

## GV-Keyboard V3 for GV-Control Center



The GV-Keyboard V3 is designed to program and operate GV-Control Center, and it can also be connected with PTZ cameras directly for PTZ control.

### Key Features

- Up to 36 GV-Control Centers supported
- Up to 8 monitors for Matrix View and ViewLog workable with multiple Keyboards
- PTZ camera control
- OSD panel supported
- Video Wall for Zoom and Scan Window control

### Specifications

OS Supported	64-bit	Windows 7 / 8 / 8.1 / Server 2008 R2 / Server 2012
System Supported	GV-Control Center V8.5 or later	
Output	USB	USB 2.0
	DVR/RS-485+ DVR/RS-485-	Connects to GV-NET card, GV-NET/IO card, GV-Hub V2 or GV-COM V2
	PTZ/RS-485+ PTZ/RS-485-	Connects to PTZ cameras
	PTZ/RS-422+ PTZ/RS-422-	
Communication	RS-485	9,600 bps (between the keyboard and GV-Control Center)
	RS-485 / 422	2,400 ~ 115,200 bps (between the keyboard and PTZ cameras)
Power	DC In	DC 12V 1A
Environmental Conditions	Operating Temperature	0~50°C / 32 ~122°F
	Humidity	5%~95% (non-condensing)
Dimensions (L x W x H)	161 x 300 x 45 mm / 6.34 x 11.81 x 1.77 in	
Quick Start Guide	<a href="#">GV-Keyboard V3</a>	

#### Note:

1. Currently, GV-Keyboard V3 does not support embedded operating systems.
2. Control of GV-Video Wall using GV-Keyboard V3 is supported by GV-Control Center V3.1.2 or later.
3. Specifications are subject to change without notice.