

## AMPLIFICADOR DE 480 W, 5 ZONAS Y FM/MP3 (USB-SD)

**A-480MZ**

**480 W**

Amplificador de 480 W RMS en línea de 100 V con

seis entradas, cinco zonas de altavoces, ajuste individual de nivel de entrada, control de volumen general, ecualizador gráfico de 7 bandas, tonos de gong y sirena... Incluye una fuente musical con radio FM y puertos SD y USB para reproducir archivos MP3. Permite la grabación desde las entradas en la tarjeta SD o memoria USB. Control remoto desde micrófono PM-5Z.



Alimentación	110/230 V CA, 50/60 Hz
Potencia	480 W RMS
Salidas zonas 1 a 5	100 V
Salida baja impedancia	4 ohm
Canales de entrada	6 (3 MIC + 3 MIC/AUX)
Prioridad	seleccionable en MIC1 y MIC2
Entradas adicionales	audio con prioridad total micrófono de zonas
Fuente musical	FM, MP3. Puerto USB / SD Bluetooth, grabación.
Respuesta en frecuencia	80 ~ 18.000 Hz
Relación señal-ruido	> 80 dB
Distorsión armónica TDH	< 0,1%
Dimensiones (mm)	420 x 88 x 320 (2 u rack)
Peso	5,50 kg

- Entradas frontales adicionales para MIC1 y AUX6.
- Entrada adicional con prioridad máxima.
- Salida de música en espera (Music on Hold)
- Prioridad seleccionable en MIC1 y MIC2.
- Alimentación phantom seleccionable para MIC1.
- Enlace con otros amplificadores.
- Conexión de procesadores de audio externos: ecualizadores, antilarsen...
- Grabación desde entradas de audio en USB / SD.
- Selectores de llamada a zona (5) y llamada general.
- Control de zonas desde pupitre microfónico PM-5Z.



### Pupitre microfónico (opcional)

#### PM-5Z

Pupitre microfónico con teclas para selección de zonas (5), llamada general, gong y para hablar.

Incorpora un control de ganancia, un interruptor para mantener abierto el micrófono y un conector RJ45 para enlazar con el amplificador.

# AMPLIFICATION

## 480 W AMPLIFIER WITH 5 ZONES AND FM/MP3 (USB-SD)

**A-480MZ** **480 W** 480 W RMS, 100 V amplifier with six inputs and five speaker output zones, individual input level adjust, master volume control, 7-band graphic equalizer, gong and siren tones ... includes a music source with radio FM and SD and USB port to play MP3 files. It allows recording from the inputs in the SD card or USB memory. Remote control from PM-5Z microphone.



Power supply	110/230 Vac, 50/60 Hz
Power	480 W RMS
Outputs zones 1 to 5	100 V / 70 V / 25 V
Low impedance output	4 ohm
Input channels	6 (3 MIC + 3 MIC/AUX)
Priorities	selectable in MIC1 and MIC2
Additional inputs	audio with total priority zone select remote microphone
Musical source	FM, MP3. USB / SD Bluetooth, recording.
Frequency response	80 ~ 18,000 Hz
Signal-to-noise ratio	> 80 dB
Harmonic distortion TDH	< 0,1%
Dimensions (mm)	420 x 88 x 320 (2 u rack)
Weight	5.50 kg

- Additional front input for MIC1 and AUX6.
- Additional rear input with maximum priority.
- Music on Hold output.
- Priority selectable in MIC1 and MIC2.
- Phantom power supply selectable for MIC1.
- Link to other amplifiers.
- Connection of external audio processors: equalisers, antilarsen...
- Recording from audio inputs to USB / SD.
- Zone selector keys (5) and all-call key.
- 5 zone select microphone desk PM-5Z.



### Microphone desk (optional)

#### PM-5Z

Microphone desk with zone selector switch for all call or individual call. Talk & chime switch.

It includes level control volume, sliding switch for lock to keep open the microphone and RJ45 connector to link with the amplifier.