

# SENSIT BACK-UP BATTERY

| battery pack for sensit gateway



#### KEY FEATURES:

- Power supply back-up battery
- Connects SENSIT Gateway to lamppost or solar panel
- Up to 35h autonomous time

#### Battery Pack

The SENSIT Back-up Battery is available to ensure the wireless SENSIT network remains operational even in case of power failure. This battery pack can be connected directly to the Gateway. This enables the Gateway to connect to a lamppost or solar panel. The battery will be charged during night time when the lamppost or solar panel is activated.

The SENSIT Back-up battery offers up to 35h of autonomous time. This ensures a reliable system under all circumstances.

# SPECIFICATIONS

Technical information	SENSIT Back-up Battery
Dimensions	250 x 90 x 250 mm [9.9 x 3.5 x 9.9 in] excluding pole mounting set
Weight	3,8 kg [134 oz]
Protection	IP65
Color	Aluminum & dark blue side covers RAL5011
Operating temperature	-15°C ... +50°C [5°F ...122°F]
Storage temperature	-15°C ... +50°C [5°F ...122°F]
Power	Internal battery, 12VDC   7Ah lead-acid
Battery runtime (without charging)	Up to 35 hours
Expected life time	> 1000 discharge/charge cycles
Part numbers	9219013 SENSIT Back-up Battery
Document version nr.	v1.1